

**Wireless Temperature/ Humidity and Activity
Detection Sensor**

R720B

User Manual

Table of Content

1. Introduction	2
2. Appearance	2
3. Main Features	3
4. Set up Instruction.....	4
5. Data Report	5
6. Control Command	6
7. Installation.....	9
8. Information about Battery Passivation	10
8.1 To determine whether a battery requires activation.....	10
8.2 How to activate the battery	10
9. Important Maintenance Instruction.....	11

1. Introduction

The R720B is a wireless temperature and humidity device with motion detection alarms for Netvox Class A type devices based on the LoRaWAN open protocol.

LoRa Wireless Technology:

LoRa is a wireless communication technology dedicated to long distance and low power consumption. Compared with other communication methods, LoRa spread spectrum modulation method greatly increases to expand the communication distance. Widely used in long-distance, low-data wireless communications. For example, automatic meter reading, building automation equipment, wireless security systems, industrial monitoring. Main features include small size, low power consumption, transmission distance, anti-interference ability and so on.

LoRaWAN:

LoRaWAN uses LoRa technology to define end-to-end standard specifications to ensure interoperability between devices and gateways from different manufacturers.

2. Appearance




Fig.1 R720B Appearance

3. Main Features

- Compatible with LoRaWAN
- 2 ER14505 lithium batteries (3.6V / section) parallel power supply
- Detectable air temperature and humidity
- Simple operation and setting
- The base is attached with a magnet that can be attached to a ferrous object
- Protection class IP65
- Compatible with LoRaWAN™ Class A
- Frequency hopping spread spectrum
- Configuration parameters can be configured via a third-party software platform, data can be read and alerts can be set via SMS text and email (optional)
- Applicable to third-party platforms: Actility/ThingPark, TTN, MyDevices/Cayenne
- Low power consumption and long battery life

Note:

Battery life is determined by the sensor reporting frequency and other variables, please refer to

http://www.netvox.com.tw/electric/electric_calc.html

On this website, users can find battery life time for varied models at different configurations.

4.Set up Instruction

On/Off

Power on	Insert batteries. (users may need a flat blade screwdriver to open)
Turn on	Press and hold the function key for 3 seconds till the green indicator flashes once.
Turn off (Restore to factory setting)	Press and hold the function key for 5 seconds till the green indicator flashes for 20 times.
Power off	Remove Batteries.
Note:	<ol style="list-style-type: none"> 1. Remove and insert the battery; the device is at off state by default. 2. On/off interval is suggested to be about 10 seconds to avoid the interference of capacitor inductance and other energy storage components. 3. Five seconds after power on, the device will be in engineering test mode.

Network Joining

Never joined the network	<p>Turn on the device to search the network.</p> <p>The green indicator stays on for 5 seconds: success</p> <p>The green indicator remains off: fail</p>
Had joined the network	<p>Turn on the device to search the previous network.</p> <p>The green indicator stays on for 5 seconds: success</p> <p>The green indicator remains off: fail</p>
Fail to join the network (when the device is on)	<p>First two mins: wake up every 15 seconds to send request.</p> <p>After two mins: enter sleeping mode and wake up every 15 minutes to send request.</p> <p>Note: Suggest to remove batteries if the device is not used to save power.</p> <p>Suggest to check the device verification information on the gateway or consult your platform server provider.</p>

Function Key

Press and hold for 5 seconds	<p>Restore to factory setting / Turn off</p> <p>The green indicator flashes for 20 times: success</p> <p>The green indicator remains off: fail</p>
Press once	<p>The device is in the network: green indicator flashes once and sends a report</p> <p>The device is not in the network: green indicator remains off</p>

Sleeping Mode

The device is on and in the network	<p>Sleeping period: Min Interval.</p> <p>When the reportchange exceeds setting value or the state changes: send a data report according to</p>
-------------------------------------	--

	Min. Interval.
The device is on but not in the network	<p>First two mins: wake up every 15 seconds to send request.</p> <p>After two mins: enter sleeping mode and wake up every 15 minutes to send request.</p> <p>Note: Suggest to remove batteries if the device is not used.</p> <p>Suggest to check the device verification information on the gateway or consult your platform server provider.</p>

Low Voltage Warning

Low Voltage	3.2V
-------------	------

5. Data Report

Data Report

The device will immediately send a report of the version package and a report data with temperature and humidity and voltage values.

The device sends data in the default configuration before any configuration is done.

Maximum time: Max Interval

Minimum time: Min Interval (by default, the current voltage value is detected every Min Interval)

Default reportchange:

Battery --- 0x01 (0.1V)

Air temperature default reportchange: 1 ° C

Air humidity default reportchange: 1%

Note: The device data reporting cycle is configured before shipment .

The interval between two reports must be the minimum time

R720B default Max Interval = 15min, Min Interval = 15min (if there is special custom shipment, the setting is changed according to customer requirements)

Please refer Netvox LoRaWAN Application Command document and Netvox Lora Command Resolver

<http://cmddoc.netvoxcloud.com/cmddoc> to resolve uplink data.

Data report configuration and sending period are as following:

Min Interval (Unit:second)	Max Interval (Unit:second)	Reportable Change	Current Change \geq Reportable Change	Current Change $<$ Reportable Change
Any number between 1~65535	Any number between 1~65535	Can not be 0.	Report per Min Interval	Report per Max Interval

6. Control Command

FPort: 0x07

Bytes	1	1	Var(Fix =9 Bytes)
	CmdID	DeviceType	NetvoxPayLoadData

CmdID– 1 bytes

DeviceType– 1 byte – Device Type of Device

NetvoxPayLoadData– var bytes (Max=9bytes)

Description	Device	CmdID	Device Type	NetvoxPayLoadData					
Config ReportReq	R720B	0x01	0x6F	MinTime (2bytes Unit:s)	MaxTime (2bytes Unit:s)	BatteryChange (1byte Unit:0.1v)	Temperature Change (2byte Unit:0.01 °C)	HumidityChange (2byte Unit:0.01%)	
Config ReportRsp		0x81		Status (0x00_su ccess)	Reserved (8Bytes,Fixed 0x00)				
ReadConfig ReportReq		0x02		Reserved (9Bytes,Fixed 0x00)					
ReadConfig ReportRsp		0x82		MinTime (2bytes Unit:s)	MaxTime (2bytes Unit:s)	BatteryChange (1byte Unit:0.1v)	Temperature Change (2byte Unit:0.01 °C)	HumidityChange (2byte Unit:0.01%)	

(1) **Command Configuration:**

MinTime = 1min 、 MaxTime = 1min 、 BatteryChange = 0.1v 、 TemperatureChange = 1°C 、 HumidityChange = 1%

Downlink: 016F003C003C0100640064 003C(H_{ex}) = 60(D_{ec}) 0064(H_{ex}) = 100(D_{ec})

Response:

816F000000000000000000000000 (Configuration success)

816F010000000000000000000000 (Configuration failure)

(2) **Read Configuration:**


Downlink: 026F000000000000000000000000

Response:

826F003C003C0100640064 (Current configuration)

Example#1 based on


MinTime = 1 Hour, MaxTime= 1 Hour, Reportable Change i.e. BatteryVoltageChange=0.1V



Note: MaxTime=MinTime. Data will only be report according to MaxTime (MinTime) duration regardless BtteryVoltageChange value.


Example#2 based on

MinTime = 15 Minutes, MaxTime= 1 Hour, Reportable Change i.e. BatteryVoltageChange= 0.1V.



Example#3 based on

MinTime = 15 Minutes, MaxTime= 1 Hour, Reportable Change i.e. BatteryVoltageChange= 0.1V.



Notes:

- 1) The device only wakes up and performs data sampling according to MinTime Interval.
When it is sleeping, it does not collect data.
- 2) The data collected is compared with the last data reported. If the data change value is greater than the ReportableChange value, the device reports according to MinTime interval.
If the data variation is not greater than the last data reported, the device reports according to MaxTime interval.
- 3) We do not recommend to set the MinTime Interval value too low. If the MinTime Interval is too low, the device wakes up frequently and the battery will be drained soon.
- 4) Whenever the device sends a report, no matter resulting from data variation, button pushed or MaxTime interval, another cycle of MinTime/MaxTime calculation is started.

7. Installation


This product comes with waterproof function. When using it, the back of it can be adsorbed on the iron surface, or the two ends can be fixed to the wall with screws.

Note: To install the battery, use a screwdriver or similar tool to assist in opening the battery cover.

1. The temperature and humidity and article movement sensor (R720B) has a built-in magnet (as shown by the dotted line in the figure below). It can be attached to the surface with iron material during installation, which is convenient and quick.

Comment

Do not install the device in a metal shielded box or in an environment surrounded by other electrical equipment to avoid affecting the wireless transmission of the device.



Temperature and humidity and article movement sensor (R720B) can be used in the following scenarios:

- Museum
- Science Museum
- Library
- Engine room
- Smart cities and buildings

Where it is necessary to detect temperature or humidity and prevent valuables from being moved illegally



2. Temperature and humidity and article movement sensors detect temperature (or humidity) according to Min Time. When the detected temperature value (or humidity value) is compared with the last report, it exceeds the set value (temperature default 1 °C; humidity default 1%). , That is, the temperature change exceeds 1 ° C (or the humidity exceeds 1%), and the currently detected value is sent.

3. When the valuables fixed with the temperature, humidity and article movement sensors are illegally moved, the temperature, humidity and article movement sensors immediately send "alarm" messages.

4. If the change value of temperature or humidity does not exceed the set value, and at the same time no movement of the item is detected, the data is reported regularly according to Max Time.

Explanation:

When the item moves, the alarm bit is "1"

When the item is stationary, the alarm bit is "0"

8. Information about Battery Passivation

Many of Netvox devices are powered by 3.6V ER14505 Li-SOCl₂ (lithium-thionyl chloride) batteries that offer many advantages including low self-discharge rate and high energy density.

However, primary lithium batteries like Li-SOCl₂ batteries will form a passivation layer as a reaction between the lithium anode and thionyl chloride if they are in storage for a long time or if the storage temperature is too high. This lithium chloride layer prevents rapid self-discharge caused by continuous reaction between lithium and thionyl chloride, but battery passivation may also lead to voltage delay when the batteries are put into operation, and our devices may not work correctly in this situation.

As a result, please make sure to source batteries from reliable vendors, and it is suggested that if the storage period is more than one month from the date of battery production, all the batteries should be activated.

If encountering the situation of battery passivation, users can activate the battery to eliminate the battery hysteresis.

ER14505 Battery Passivation:

8.1 To determine whether a battery requires activation

Connect a new ER14505 battery to a resistor in parallel, and check the voltage of the circuit.

If the voltage is below 3.3V, it means the battery requires activation.

8.2 How to activate the battery

- a. Connect a battery to a resistor in parallel
- b. Keep the connection for 5~8 minutes
- c. The voltage of the circuit should be ≥ 3.3 , indicating successful activation.

Brand	Load Resistance	Activation Time	Activation Current
NHTONE	165 Ω	5 minutes	20mA
RAMWAY	67 Ω	8 minutes	50mA
EVE	67 Ω	8 minutes	50mA
SAFT	67 Ω	8 minutes	50mA

Note:

If you buy batteries from other than the above four manufacturers, then the battery activation time, activation current, and required load resistance shall be mainly subject to the announcement of each manufacturer.

9.Important Maintenance Instruction

Your device is a product of superior design and craftsmanship and should be used with care. The following suggestions will help you use the warranty service effectively.

- Keep the equipment dry. Rain, moisture, and various liquids or moisture may contain minerals that can corrode electronic circuits. In case the device is wet, please dry it completely.
- Do not use or store in dusty or dirty areas. This can damage its detachable parts and electronic components.
- Do not store in excessive heat. High temperatures can shorten the life of electronic devices, destroy batteries, and deform or melt some plastic parts.
- Do not store in a cold place. Otherwise, when the temperature rises to normal temperature, moisture will form inside, which will destroy the board.
- Do not throw, knock or shake the device. Rough handling of equipment can destroy internal circuit boards and delicate structures.
- Do not wash with strong chemicals, detergents or strong detergents.
- Do not apply with paint. Smudges can block debris in detachable parts and affect normal operation.
- Do not throw the battery into a fire to prevent the battery from exploding. Damaged batteries may also explode.

All of the above suggestions apply equally to your device, battery and accessories.

If any device is not working properly, please take it to the nearest authorized service facility for repair.